

SUNNY MONDAY SPECIALS



Santa Suggests for Christmas The New Gerhard Heintzman Combination Radio and Phonograph

It is beautifully designed, console model, Queen Anne style, with an automatic phonograph start and stop. The Radiola IIIA is a very high-grade instrument and is well recommended by leading authorities. It may be obtained in either walnut or mahogany and at a very attractive price. Easy terms can be arranged.

Have One In Your Home This Christmas.

Gerhard Heintzman
LIMITED
222 DUNDAS STREET (Near Clarence Street)

Now Available
Model 80
His Master's Voice Victrola
at
Mason & Risch

With great pleasure Mason & Risch announce the arrival of a limited number of "His Master's Voice" Victrolas Model 80.

TO MOVE THEM FAST—this limited stock is offered on the easy terms of

\$10 DOWN

and the balance in small
Weekly or Monthly
payments.

Now there is no excuse to accept a substitute for this world-famous instrument—Those who ACT quickly may own a genuine Victrola—famed the world over at

Mason & Risch
248 DUNDAS STREET.
London's Largest and
Leading Music
House.

Advertise in The Advertiser

NEW FLIVVER RADIO SET EASY TO MAKE, EFFICIENT

Long Signals and Long Distance Possible With Simple Hookup.

USE PEANUT TUBE

W. B. CARTMEL, B.S., M.A., M.E.I.C. Probably the simplest and most efficient set for a beginner to make up is the new Flivver. This set gives loud signals and long distance reception. The apparatus required is simple and the wiring of the set is easily done. There is only one coil required and it has no movable parts. The coil is made of winding 110 turns of No. 28 gauge double cotton-covered wire on a 3-inch tube with a tap at 75 turns. Bakelite tubing may be used, but just as good results will be given with ordinary cardboard tubing, provided it is dry.

Some prefer to shellac the tube inside and out before winding it, but be sure the shellac is very dry before winding on the wire. Make two pinholes half an inch apart, both of them about half an inch from one end of the tube. Push your wire down through one of these holes and cut through the other and then go ahead and wind your coil. When you have wound 75 turns, take off a tap and then continue winding 35 more until the complete 110 turns have been wound on. When the end of the wire may be again secured by weaving the end of the wire in and out of

Italian Deputy Shot In Duel



Associated Press Despatch.

Turin, Italy, Nov. 14.—A duel was fought today at Vercelli between the Fascist deputy, Belloni, and the Liberal deputy, Rossini, in which Rossini was wounded six times. Belloni was untouched. The combatants remained unreconciled after the meeting at arms, which was due to alleged insulting epithets applied by the Liberal deputy to Deputy Belloni.

two more holes similar to those at the beginning of the coil.

List of Parts.

- The apparatus required is as follows:
- 1 coil having 110 turns of No. 28 gauge double cotton-covered magnet wire, wound onto 3-inch tube and tapped at 75 turns.
 - 2 No. R500 or No. R62-B condensers (23 plate).
 - 1 No. R215-A peanut tube.
 - 1 No. R40 socket for peanut tube.
 - 1 No. R53-C grid condenser, .00015 MF.
 - 1 No. R42-C grid leak (2 megohms).
 - 1 No. R-CH-2 rheostat.
 - 1 No. R28 binding posts.
 - 1 No. R6 head set.



One Day Specials In Warm Wearables

Distinct savings on every one of these items, which are positively for Monday only—No phone orders.

MEN'S HEAVY WOOL SWEATER COATS with collar and pockets; regular \$2.25; all sizes, for **\$1.48**

BOYS' V-NECK WOOL PULLOVER SWEATERS in Royal Blue with contrast trim; sizes 24 to 32 **\$1.39**

Broken lot of **MEN'S HEAVY FLEECE-LINED SHIRTS AND DRAWERS**; Reg. 89c and 98c, for **69c**

Men's HEAVY ALL-WOOL RIBBED SHIRTS AND DRAWERS; unshrinkable, in all sizes **\$1.50**

BOYS' ALL-WOOL MACKINAW

Boys' All Wool Mackinaw Coats, Norfolk style, in splendid colors and patterns; sizes 26 to 32 **\$4.98**

MEN'S MEDIUM-WEIGHT RIBBED COMBINATIONS, sizes 36, 40 and 42 **\$1.48** only; Reg. \$2.50.

Men's Heavy Blue and White Stripe Overalls with bib and braces, all sizes; worth \$2 **\$1.48**

MEN'S \$25 GRAY MELTON OVERCOATS.

Fine All Wool Dark Gray Melton Overcoats in single-breasted, Chesterfield or standard models; sizes 35 to 40 only; regular \$25, for **\$19.75**

R. J. Young & Co. Ltd.

1 22½-volt battery (Eveready No. 764 or No. 765).
1 dry cell (Eveready No. 7111).
It will be noted that all the battery required is a single 1½-volt dry-cell and one small size 22½-volt battery. The 1½-volt dry-cell will give considerably more than one hundred hours of actual use, while the B battery should give service for two hours a day for a year. The small battery requirements make this a very portable set.

Peanut Tube Is Urged.

In the above apparatus I would especially emphasize the use of the peanut tube in order to get good results. Do not use some makeshift socket but the regular R40 socket, which is made for the tube. I would also recommend a good fixed grid leak and grid condenser as called for. The grid leak and grid condenser are the last things that one should economize on, because much of the performance of the set depends on these two pieces of apparatus and even the very best grid leak and grid condenser are not costly. The baseboard should be of dry wood. The panel should be of hard rubber or of any of the various types of panel material that are on the market; size 6x12 inches should do very well. A good dry wood panel will be found very satisfactory. Either bare bus wire or rubber-covered wire may be used for wiring the set.

Shielding.

It will be noted that a shield is shown between the panel and the tuning condenser. This shield consists of a metal plate a few inches square, which may be ordinary tin or other thin sheet metal. The feed-back condenser may be shielded also if desired. It will be noted that the ground wire is soldered to this shield.

How to Tune the Set.

After properly connecting the batteries, aerial and ground wire, turn on your filament current by means of the vernier rheostat. Begin with both of your condensers at zero. It should be mentioned that your dials should be so adjusted that when you read zero the plates of your condensers are all out, and when your dial reads 100 the rotary plates are completely meshed within the fixed plates. Having both of your condensers set at zero turn the feed-back condenser until a slight hissing noise is heard in the speaker. Now turn on your tuning condenser and you will notice that the hissing noise disappears, and then turn on your feed-back condenser a little more until you hear the hissing noise again. As a matter of fact it is desirable to turn the two condensers together. Begin by reducing the slight hissing noise by means of the feed-back condenser and then as you turn on your tuning condenser follow up with the feed-back condenser turning the two condensers together so as to keep the set just at the hissing point.

As your tuning condenser is moved you will note that the stations you will hear different stations come in with a zip. If there is a whistle as you pass a station your feed-back is turned on too much and it should be turned back a little. It is very important to take great care you do not have enough feed-back so that you pass stations with a whistle. Any whistle that you produce in your set will make a whistle in your neighbor's set. Those who live in large cities should be very careful about this, as they may cause considerable annoyance to their neighbors, and furthermore, the set will give the loudest signals and the longest distance reception if it is kept just below the whistling point.


How to Do Fine Tuning With Set.

Having found your station in the manner outlined above, turn your tuning-knob back and forth past the station and if you notice any sign of a whistle turn back your rheostat until the whistle disappears. Then turn on a little more current by means of the vernier adjustment, and as you do you will notice the signal get louder. If you turn it on too much the tube will pull over into an oscillating condition, and you will bring in whistles again and the signals will not be so loud. In that case turn back the vernier rheostat and then turn it on again gradually until you are set to the very loudest point. In this way you will get the most distant reception. Do not let your tube oscillate, because an oscillating condition spoils the music both for yourself and for your neighbors.

PLAN AGRICULTURAL COURSE.

Special to The Advertiser.
Brussels, Nov. 14.—The O. A. C. Guelph is planning a short course in agriculture to be held in Brussels during the months of December, January and February.

ROTAREX ELECTRIC WASHERS



In the big, 10-pound aluminum ROTAREX cylinder the clothes glide without friction over a glassy surface that is free from perforations. The cleansing suds are suctioned into the self-reversing, revolving cylinder through numerous holes in its two ends or heads. It is the only Washer made that does not wash back into the clothes the same dirt that it washed out of them. This cylinder type Washer is used by all laundries and institutions the world over. Washes a few clothes as well as a tubful.

ARCHER ELECTRIC
221 Dundas Street. — (East of Clarence Street).


ONLY FIVE WEEKS TILL CHRISTMAS

Give Santa Claus Your Order

—FOR A—

Red Bird Bicycle

And it will be delivered any time you desire between now and Christmas Eve.



This is the season when dear old dad, the regular fellow, can give the kiddies the long-wished-for RED BIRD—the Bicycle that makes hearts happy and develops buoyant health and vigor.

We give the kind of terms you like—so don't hesitate, but come in right away and talk things over.

Bicycle and Motor Sales Company

425 WELLINGTON STREET.

PHONE 3182.

G. A. WENIGE, the Man Who Made Walking Expensive.

NOBEL WINNER AROSE FROM PEASANT RANKS

Checked Career of Reymont Brings Tim to Peak of Literature Fame.

Associated Press Despatch.

Warsaw, Nov. 14.—Wladislaw Reymont, the Polish writer, who has been awarded the 1924 Nobel prize in literature, received notice of the honor while here recovering from a serious attack of pneumonia. M. Reymont was born in 1868 and belonged to a peasant family which took an active part in the Polish revolution against Russia in 1863. His anti-Russianism resulted in his expulsion from the Russian teachers from the school at Kielec, and he started work, though very young, as a telegraph operator in a small railroad station. Later he joined a travelling theatrical company and then drifted to other occupations, at one time being a railroad worker and another a farm hand. He once went to the famous Polish cloister at Czestochowa, intending to become a monk. His first stories were published in magazine form in 1893.

His most famous work, the novel "Pensées," issued in four volumes—"Autumn," "Winter," "Spring" and "Summer," has been translated into all the European languages.

M. Reymont is wealthy and has an estate near Posen.

MENTAL HYGIENE BODY OPENS CONFERENCE

Canadian Press Despatch.

Montreal, Nov. 14.—The annual meeting of the Canadian national committee for mental hygiene began here this morning with a meeting of the executive in the medical building of McGill university. A report was prepared to submit to the board of directors this afternoon. A luncheon for the board and delegates from the various provinces was held in a local hotel, after which the board met to consider recommendations for submission to the annual meeting, which begins at 4:30 p.m.

MONDAY SPECIALS

Sweet Potatoes;	25c	Bulk Tea;	60c
3 lbs.		lb.	
Beef Cuttings;	25c	Home-made Shorten-	30c
3 lbs.		ing; 2 lbs.	
Washing Soda;	25c		
3 pkgs. for			

ANDERSONS—The Big Store

Phones, 1643-1644. Deliveries 8, 9, 11, 2 and 4.

Who Wants Car Value In — USED CARS

—Here It Is!

We are not stating prices—we guarantee you a square deal. Come and see them and we'll give you a fair price on the one you select.

Essex Coach, 1923.	Overland Coupe, 1922.
Hudson Coach, 1923.	Essex Tour., 4 cyl., 1923.
Hudson Coach, 1922.	Essex Touring, 1922.
Hudson Coupe, 1920.	Dodge Touring, 1922.
Paige Sedan, 1922.	McLaughlin, 1920.
McLaughlin Sedan, 1923.	International 2-ton truck.
New Olds. 6 Sedan, \$1,600	Olds. truck.

A. H. Burrows

Hudson and Essex Dealer.

90 YORK ST.

—:—

PHONE 2172-M.

Advertise in The Advertiser